

1) Tightening torque



## Basic features

Approval/Conformity	CE UKCA cULus WEEE FCC (Radio) IC (Radio) KC ETA NBTC IFT
EN 301489-1/-3	EN55022 (Class A)
Principle of operation	Processor unit

## Display/Operation

Function indicator	Run EtherCAT, LED green Ready, LED green Error EtherCAT, LED red Link/Activity ECAT Out, LED green Link/Activity ECAT In, LED green
--------------------	-------------------------------------------------------------------------------------------------------------------------------------------------

## Electrical connection

Connection (COM 1)	ECAT In: M12x1-Female, 4-pin, D-coded
Connection (COM 2)	ECAT Out: M12x1-Female, 4-pin, D-coded
Connection (IO-Link/Service)	M12x1-Female, 5-pin, A-coded
Connection (supply voltage IN)	M12x1-Male, 5-pin
Connection slots	H1: M12x1-Female, 5-pin H2: M12x1-Female, 5-pin H3: M12x1-Female, 5-pin H4: M12x1-Female, 5-pin
Connector port 01, note type	for all VU/VM/VL-3... with connector, 4-pin and C-3... with adapter

## Electrical data

Current consumption max. at 24 V DC	2 A
Current consumption max. at 24 V DC without load	150 mA
IO-Link function	Master (max. 500 mA)
Nominal voltage	24 VDC
Operating voltage $U_b$	24 V DC LPS Class 2
Residual ripple max.	10 %

## Environmental conditions

Altitude max.	2000 m
Ambient temperature	0...60 °C
Area of operation	Indoor
Contamination scale	2
Continuous shock load	yes
EN 60068-2-27, Shock	yes
EN 60068-2-32 Free fall	yes
EN 60068-2-6, Vibration	yes
IP rating	IP65, with connector
Relative humidity	0...90 %, non-condensing

## Remarks

When installing, the technical standards and regulations of the corresponding countries must be observed.  
Values are under rated conditions unless otherwise specified.

Current consumption when 4 read/write heads and IO-Link device are connected to the IO-Link port max. 2 A

This device is intended to be supplied by a UL-listed or CSA-certified power supply unit with "Class 2" or LPS power source.

The devices must be installed permanently.

1. Determine a suitable mounting position.

2. Fasten the device with suitable mounting material.

The device can be cleaned with a slightly damp cloth.

Regularly check the function of the device and all associated components through visual and functional tests.

- Shut down the device in the event of malfunctions.

- Secure the system against unauthorized use.

- Check fastening and tighten if necessary.

The product is maintenance-free.

For more information about MTTF and B10d see MTTF / B10d Certificate

Indication of the MTTF- / B10d value does not represent a binding composition and/or life expectancy assurance; these are simply experiential values with no warranty implications. These declared values also do not extend the expiration period for defect claims or affect it in any way.

## Functional safety

MTTF (40 °C)	37.9 a
--------------	--------

## Interface

Auxiliary interfaces, number	1x IO-Link
IO-Link version	1.1
Interface	EtherCAT


## Material

Housing material	Zinc, Die casting
------------------	-------------------

## Mechanical data


Application weight	750.00 g
Dimension	48 x 62 x 172 mm

## Connector Drawings




- 1) 2)  
**IO-Link/ Service**  
 1 — VP (+ 24V DC)  
 2 — USB-  
 3 — 0V  
 4 — Q/C (IO/Link)  
 5 — USB+

- 1) View towards connector  
 2) Female 5-pin/ Function




- 1) 2)  
**H1...H4**  
 1 — VP (+24V DC)  
 2 — A (RS485)  
 3 — 0V  
 4 — B (RS485)  
 5 — N.C.

- 1) View towards connector  
 2) Female 5-pin/ Function



- 1)  
**ECAT In/Out**  
 2)  
 1 — +TX  
 2 — +RX  
 3 — -TX  
 4 — -RX

- 1) View towards connector  
 2) Female  
 3) Coding D



- 1)  
**Power**  
 2)  
 1 — +24V DC  
 2 — n.c.  
 3 — 0V  
 4 — n.c.  
 5 — FE