h3

3

-A

L3

Æ

L4





C

(z)

DPAK3 (TO-252 3 LD)CASE 369AS **ISSUE A**

DATE 28 SEP 2022

NOTES: UNLESS OTHERWISE SPECIFIED

- A) THIS PACKAGE CONFORMS TO JEDEC, TO-252,
- ISSUE C, VARIATION AA.
- B) ALL DIMENSIONS ARE IN MILLIMETERS.
- C) DIMENSIONING AND TOLERANCING PER ASME Y14.5M-2009.
- D) SUPPLIER DEPENDENT MOLD LOCKING HOLES OR CHAMFERED CORNERS OR EDGE PROTRUSION.
- FOR DIODE PRODUCTS, L4 IS 0.25 MM MAX.
- F) DIMENSIONS ARE EXCLUSIVE OF BURRS,
- MOLD FLASH AND TIE BAR EXTRUSIONS.
- G) LAND PATTERN RECOMMENDATION IS BASED ON IPC7351A STD TO228P991X239-3N.


DIM

L

11

L2

L3



Α 2.18 2.39 Α1 0.127 0.00 0.89 b 0.64 0.77 b2 0.76 0.95 1.14 b3 5.21 5.34 5.46 0.61 С 0.45 0.53 c2 0.45 0.52 0.58 D 5.97 6.10 6.22 D1 5.21 Ε 6.35 6.54 6.73 E1 2.286 BSC е e1 4.572 BSC Н 9.40 9.91 10.41

1.40

0.89

1.59

2 90 RFF

0.51 BSC

1.08


1.78


MIN.


MILLIMETERS

NOM. MAX.

DETAIL A (ROTATED -90°) SCALE: 12X







GENERIC MARKING DIAGRAM*

XXXXXX XXXXXX **AYWWZZ**

XXXX = Specific Device Code

= Assembly Location Α

WW = Work Week = Assembly Lot Code *This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "■", may or may not be present. Some products may not follow the Generic Marking.

LAND PATTERN RECOMMENDATION

*FOR ADDITIONAL INFORMATION ON OUR PB-FREE STRATEGY AND SOLDERING DETAILS, PLEASE DOWNLOAD THE ON SEMICONDUCTOR SOLDERING AND MOUNTING TECHNIQUES REFERENCE MANUAL SOLDERRM/D

,		3 11/1/10/12, 002521/1/1/10/5.	
DOCUMENT NUMBER:	98AON13810G	Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.	
DESCRIPTION:	DPAK3 (TO-252 3 LD)		PAGE 1 OF 1

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.